



Maestro

Smart LED Grow Light
Full Spectrum Tunable
(MAESTRO-FC-240-84-1-80-SM-1)

QUICK INSTALL GUIDE

HARDWARE INSTALLATION:

1. Remove light fixture from box.
2. Verify that serial number matches box sticker before install
3. Ensure that fixture Hook is screwed in fully
4. Ensure that install location device is installed correctly
5. Install fixture by hanging fixture by inserting fixture hook into the hanging device
6. Inspect fixture install
7. Connect power cord to electrical outlet or junction box (Line Voltage: 100VAC – 277VAC)

Note: If outlet is used with plug to provide power to the fixture then install can be completed by end user. However, if junction box is to be used to provide power you must have a certified Electrician complete power connection.

8. After power is connected energize fixture and ensure that fixture is powering on
9. If power up is successful proceed to Software section



SOFTWARE INSTALLATION:

1. Go to Phone or Tablet
2. Navigate to appropriate App store
Android: Google Play Store or
iPhone or iPad: Apple Store or
alternatively navigate to <https://avi-on.com/download>
3. Download and Install the AVI-ON App
4. Open web browser navigate to <https://support.avi-on.com/hc/en-us> for further instructions for Tune / AVI-ON controls setup and usage



TUNE ENTERPRISES, INC.

TuneGrowLights.com
P: (415) 725-6505

3500 W. Garry Ave,
Santa Ana, CA 92704 USA